

Mercusys MR80X AX3000 Dual-Band Wi-Fi router



2976Mb/s, IEEE 802.11a/b/g/n/ac/ax (Wi-Fi 6), WAN (1Gb/s): 1 port, LAN (1Gb/s): 3 port, antennák száma: 4db, 5dBi, fekete

Cikkszám: MR80X

Ár:

20 590 Ft

Garancia: 3 Év

Wireless Standards

Compatible with 802.11ax/ac/a/b/g/n Wi-Fi standards

WiFi Speeds

2402 Mbps (5 GHz) + 574 Mbps (2.4 GHz)

Reception Sensitivity

11g 6Mbps: -97dBm
11g 54Mbps: -79dBm
11n HT40 MCS7:-74dBm
11n HT20 MCS7:-77dBm
11a 6Mbps: -97dBm
11a 54Mbps: -79dBm
11ac VHT20 MCS8:-75dBm
11ac VHT40 MCS9:-71dBm
11ac VHT80 MCS9:-67dBm
11ax VHT20 MCS11:-67dBm
11ax VHT40 MCS11:-64dBm
11ax VHT80 MCS11:-61dBm

Transmission Power

2.4 GHz < 20dBm (EIRP)
5 GHz < 23dBm (band1? band2)
5 GHz < 30dBm (band3)

Wireless Security

WEP, WPA / WPA2-Personal, WPA2 / WPA3-Personal

Wireless Functions

Enable/Disable Wireless Radio, WMM

Wireless

WAN Type

Dynamic IP/Static IP/PPPoE/L2TP/PPTP

Management

Access Control
Local Management
Remote Management

DHCP

Server, DHCP Client List

NAT Forwarding

Port Forwarding, Port Triggering, UPnP, DMZ

Firewall Security

SPI Firewall, IP and MAC Address Binding

Guest Network

2.4 GHz Guest Network, 5 GHz Guest Network

VPN Sever

OpenVPN, PPTP supported

Software

Dimensions

8.2 × 6.8 × 1.6 in
(208.8 × 171.6 × 41.7 mm)

Interfaces

1× Gigabit WAN Port + 3× Gigabit LAN Ports

Button

Reset/WPS Button

Antenna Type

4× 5 dBi Fixed Omni-Directional Antennas

Hardware

Package Contents

- AX3000 Wi-Fi 6 Router MR80X

- Power Adapter
- Quick Installation Guide
- RJ45 Ethernet Cable

Environment

- Operating Temperature: 0°C~40°C (32°F~104°F)
- Operating Humidity: 10%~90% Non-Condensing
- Storage Humidity: 5%~90% Non-Condensing

Others

Gyártó

Mercusys